

Modelo: PDUG21332A-DG

PDU Conmutada

Entrada: Conector Cetac

Trifásica 32 Amperios Macho

3 metros de longitud



Plug



1 x C19 + 7 x C13



1 x C19 + 7 x C13



1 x C19 + 7 x C13

En total: 3 Salidas C19 Hembra + 21 Salidas C13 Hembra

La PDU conmutada proporciona control manual remoto de los dispositivos críticos mediante navegador web con Smartphone o PC. Detenga el dispositivo problemático cortando la alimentación a una o varias tomas de corriente específicas. Al apagar y reiniciar el dispositivo de forma remota, ahorra tiempo y dinero al eliminar la necesidad de enviar técnicos a la ubicación.

Los administradores pueden monitorear la información total del uso de energía de la PDU desde el extremo remoto a través de Internet para comprender completamente el consumo de energía de todos los dispositivos. Configure alertas de eventos de sobrecarga y notifique a los gerentes por correo electrónico y TRAP, lo que les permitirá responder a las crisis en el menor tiempo posible para minimizar inconvenientes.

La PDU conmutada tiene un puerto adicional de sensor ambiental que rastrea la información climática, variables ambientales de temperatura y humedad. Los datos están disponibles desde cualquier navegador web y son compatibles con SNMP para facilitar el seguimiento de datos críticos sin el uso de ningún software externo adicional.

Se proporciona software de administración central, que puede administrar una gran cantidad de información de energía, temperatura y humedad de las PDU. La base de datos almacena el consumo de energía.

Features:

System Function:

- Built-in embedded system:
Support 10M Ethernet interface, provides webpage and SNMP remote management.
- Multiple protocols:
Support ICMP, ARP, IP, TCP, UDP, DHCP, HTTP, NTP, SNMP v1.
- Local display information:
Seven-segments can display current, IP address and temperature and humidity values.

Power Management:



Remote Monitor

Remote monitoring PDU status by web and SNMP



Remote Control

Remote per outlet on/off by web and SNMP.




Current Measurement

Measure PDU total current consumption.



Mail Notification

Notify specified user by mail and SNMP when outlet action or current over threshold.



Threshold Sensing

User-definable warning and overload threshold value as the basis for alarm.



Event Alert

When current exceeds the preset threshold, PDU will beep and LED will flash.



Power Sequence

User-definable power on/off sequence time.



Schedule Control

Timed & scheduled on/off/reboot control.



Ping Event Control

When the specified IT device does not respond to PING, the output will perform a preset power action.



Overload Protection

When overload, circuit breaker will automatically trip to protect the safety of electricity.



Group Control

Set multiple outlets as a single group while controlling the power output.



Environment Detection

Optional accessory probe to detect temperature and humidity.



Central Management

Free centralized monitoring software, real-time monitoring of a large number of PDU, provide data records and history chart.



Specification

Output		Input	
Voltage	200-240 VAC	Voltage	200-240 VAC
Max. Current	32 A	Frequency	50/60Hz, full range
Outlet	(21) C13, (3) C19	Max. Capacity	7680 VA
ON/OFF Ind.	(24) Green LED	Connection	IEC309, power cord, 3 m
Circuit Ind.	(3) Red LED		
Overload Protection	(3) 16A UL1077 breaker		
Measurement		Other	
Current	+/-2%+/-0.1A @0.2A ~ 20 A	Ethernet	(1) RJ45
		ENV Connection	(1) RJ11
		Function Selection	(1) Button
		DHCP Ind.	(1) Green LED
		Info. Display	4 digits of 7 Segments
Dimension/Weight		Operation	
Size	1778 x 56 x 44 mm	Operation Temp.	0 ~ 45°C
Weight	6 kg	Operation Humid.	0% ~ 90% RH
Package Size	1890 x 220 x 110 mm	Storage Temp.	-20°C ~ 65°C
Package Weight	7.2 kg	Storage Humid.	0% ~ 90% RH
Approval			
Certification	CE		
Warranty	2 years		

Package

No.	Description
1	PDU 1 set
2	Rack mount accessories 1 set
	
3	Software, manual, MIB by link below

Optional Accessory

Model Name
Temp./Humidity probe

C13 socket protection

C19 socket protection


Line Drawing

